

**B O N N E V I L L E**  
**P O W E R   A D M I N I S T R A T I O N**



**Available Transfer Capability  
Implementation Document  
(MOD-001-1a)**

**Bonneville Power Administration  
Transmission Services**

**Effective Date: October 19, 2022**

---

## Contents

I. Purpose .....	1
II. Definitions .....	1
III. Overview .....	2
<b>Methodologies Selected</b> .....	2
MOD-029-2a .....	2
MOD-008-1 .....	2
<b>Methodologies Not Applicable to BPA</b> .....	2
<b>ATC Calculations</b> .....	2
ATC Calculation Periods .....	2
Frequency of ATC Recalculation.....	2
Limiting Assumptions.....	3
IV. Allocation Processes .....	3
V. Outages .....	4
<b>Outage Planning</b> .....	4
<b>Outage Criteria for TTC Calculations</b> .....	4
VI. Priorities Used to Set TTC .....	4
VII. Rated System Path Methodology for BPA’s Paths.....	5
<b>BPA’s Paths</b> .....	6
<b>Calculating TTC</b> .....	10
Data and Assumptions.....	10
Process to Determine TTC.....	11
<b>Calculating Firm Transmission Service for Paths</b> .....	13
Calculating Firm Existing Transmission Commitments (ETC <sub>F</sub> ) .....	13
Determining base ETC for Flow-Based Paths.....	15
Calculating Interim ETC <sub>F</sub> for Flow-based Paths.....	19
Calculating Firm Available Transfer Capability (ATC <sub>F</sub> ) .....	21
<b>Calculating Non-Firm Transmission Service for BPA’s Paths</b> .....	24
Calculating Non-Firm Existing Transmission Commitments (ETC <sub>NF</sub> ) .....	24
Calculating Non-Firm Available Transfer Capability (ATC <sub>NF</sub> ) .....	25
<b>Adjustments to Flow-based Path ATC Values</b> .....	31
VIII. Data Sources and Recipients.....	31
IX. Responding to Data Requests.....	32
X. ATCID Revisions.....	33

---

## 3 I. Purpose

---

4 This Available Transfer Capability Implementation Document (ATCID) addresses all of the  
5 requirements of North American Electric Reliability Corporation (NERC) Reliability Standard  
6 MOD-001-1a (Available Transmission System Capability). This ATCID is specifically required by  
7 MOD-001-1a, R3 and its sub-requirements. This ATCID also outlines BPA's Postback  
8 Methodology as required by North American Energy Standards Board (NAESB) Wholesale  
9 Electric Quadrant business practice standards.

10 This ATCID only applies to ATC calculations through month 13.

---

## 11 II. Definitions

---

12 All capitalized terms used in this ATCID are either contained in NERC's Glossary of Terms,  
13 NAESB WEQ-000, or are defined in this ATCID.

14 Defined terms specific to BPA include:

- 15 • **Federal Columbia River Power System (FCRPS):** The Transmission System  
16 constructed and operated by BPA and the 31 federally-constructed hydroelectric dams<sup>1</sup>  
17 on the Columbia and Snake Rivers, and the Columbia Generating Station nuclear plant.  
18 Each entity is separately managed and financed, but the facilities are operated as an  
19 integrated power System.
- 20 • **Federal Columbia River Transmission System (FCRTS):** The FCRTS is comprised of  
21 BPA's main grid network Facilities (Network), Interconnections with other  
22 Transmission Systems (External Interconnections<sup>2</sup>), Interties,<sup>3</sup> delivery Facilities,  
23 subgrid Facilities, and generation Interconnection Facilities within the Pacific  
24 Northwest region and with western Canada and California.
- 25 • **Long-Term Reservation:** a confirmed reservation that has duration greater than or  
26 equal to 365 days
- 27 • **Short-Term Reservation:** a confirmed reservation that has duration less than 365  
28 days

---

<sup>1</sup> Albeni Falls, Anderson Ranch, Big Cliff, Black Canyon, Boise River Diversion, Bonneville, Chandler, Chief Joseph, Cougar, Detroit, Dexter, Dworshak, Foster, Grand Coulee, Green Peter, Green Springs, Hills Creek, Hungry Horse, Ice Harbor, John Day, Libby, Little Goose, Lookout Point, Lost Creek, Lower Granite, Lower Monumental, McNary, Minidoka, Palisades, Roza and The Dalles

<sup>2</sup> Northern Intertie, Reno-Alturas Transmission System, West of Hatwai, West of Garrison and LaGrande paths.

<sup>3</sup> AC Intertie (NWACI), Pacific DC Intertie, and Montana Intertie.

---

## 29 III. Overview

---

30 BPA owns and provides Transmission Service over the FCRTS. BPA is registered with NERC as a  
31 Transmission Operator (TOP) and Transmission Service Provider (TSP), among other  
32 registrations.

### 33 Methodologies Selected

#### 34 MOD-029-2a

35 BPA has elected to use the Rated System Path Methodology (MOD-029-2a) to calculate  
36 Available Transfer Capability (ATC) for its paths. The description of how BPA implements  
37 this methodology for these paths is included in this ATCID. (MOD-001 R1)

#### 38 MOD-008-1

39 BPA maintains Transmission Reliability Margin (TRM) as described in NERC Standard MOD-  
40 008-1 for its Northern Intertie, West of Garrison E>W and Satsop Injection paths. The  
41 description of how BPA implements TRM can be found in BPA's TRM Implementation  
42 Document (TRMID), found on BPA's website. BPA does not maintain TRM for any other  
43 paths.

### 44 Methodologies Not Applicable to BPA

45 BPA does not use the Area Interchange Methodology (MOD-028-2), the Flowgate  
46 Methodology (MOD-030-2), or a Capacity Benefit Margin (MOD-004-1). Therefore, these  
47 standards are not applicable to BPA.

### 48 ATC Calculations

#### 49 ATC Calculation Periods

50 BPA calculates ATC values using the Rated System Path Methodology for the following time  
51 periods: (MOD-001 R2)

- 52 • Hourly values for up to 168 hours. The next hour may be calculated in subhourly  
53 intervals, with the most limiting subhourly ATC value being the hourly value. (MOD-001  
54 R2.1)
- 55 • Daily values for day 3 through day 90. For days 3 to 7 (up to hour 168), the daily ATC  
56 value is the most limiting hourly ATC value for that day. (MOD-001 R2.2)
- 57 • Monthly values for month 2 through month 13. For months 2 and 3 (up to day 90), the  
58 monthly ATC value is the most limiting daily ATC value for that month. (MOD-001 R2.3)

#### 59 Frequency of ATC Recalculation

60 BPA recalculates ATC on the following frequency, even if the calculated values  
61 identified in the ATC equation are unchanged: (MOD-001 R8)

- 62 • Hourly, at least once per hour. (MOD-001 R8.1)
- 63 • Daily, at least once per day. (MOD-001 R8.2)

64 • Monthly, at least once per day. (MOD-001 R8.3)

65 BPA may recalculate ATC values more frequently due to changes in Total Transfer  
66 Capability (TTC), Power Transfer Distribution Factors (PTDFs), system issues or as deemed  
67 necessary.

#### 68 **Limiting Assumptions**

69 BPA studies assumptions of various System conditions to develop TTCs for its paths for the  
70 planning of operations time frame. The governing TTCs for each time frame are  
71 established from these planning of operations studies, based on the time period being  
72 calculated and the reason for the change in TTC. BPA uses these TTCs in its ATC  
73 calculations. There are no additional TTC studies conducted to establish the path TTCs  
74 used BPA's ATC calculations. Therefore when determining the TTC, BPA studies  
75 assumptions that are no more limiting than those used in its planning of operations for the  
76 corresponding time period, when such planning of operations has been performed for that  
77 time period. (MOD-001 R6)

78 When calculating ATC, BPA uses the TTCs determined in its planning of operations TTC  
79 studies. There are no additional TTC studies conducted to establish the path TTCs used in  
80 BPA's ATC calculations. For flow-based paths, BPA calculates Existing Transmission  
81 Commitments (ETC) by summing base ETC from power flow studies with interim ETC from  
82 PTDFs. BPA uses the most recent System condition information to re-calculate its hourly,  
83 daily and monthly PTDFs in the planning of operations time frame. The ETCs used in  
84 BPA's ATC calculations are re-calculated with these updated PTDFs in each time frame.  
85 There are no additional ETC studies, beyond the base ETC studies and the PTDF  
86 calculations, performed during the planning of operations time frame. Therefore, BPA  
87 does not use more limiting assumptions when calculating ATC in its planning of operations  
88 time frame. (MOD-001 R7)

---

## 89 **IV. Allocation Processes**

---

90 BPA allocates transfer capability among multiple owners or users of its 1:1 and flow-based  
91 paths.

### 92 **Allocating TTC:**

93 For paths where allocation agreements exist, BPA allocates TTC according to the  
94 contractual rights of the various owners as defined in the agreements.

95 Allocation agreements do not exist for three of BPA's flow-based paths that have multiple  
96 owners: South of Allston S>N, Columbia Injection N>S and Wanapum Injection N>S. BPA  
97 uses the allocations found in the South of Allston N>S agreement to allocate TTC across  
98 South of Allston S>N. For Columbia Injection N>S and Wanapum Injection N>S, BPA  
99 determines its share of TTC based on BPA-owned transmission lines that make up these  
100 paths when all lines are in service. During outage conditions, individual allocations exist  
101 for the loss of each transmission line in the line definitions for these paths.

102

## 103 **Allocating base ETC:**

104 BPA also allocates its base ETC among some of its shared flow-based paths. To allocate  
105 base ETC for South of Allston N>S and S>N, BPA uses the contractual rights defined in the  
106 South of Allston allocation agreement. To allocate base ETC for the Columbia Injection  
107 N>S and Wanapum Injection N>S paths, BPA only models BPA's lines in the base ETC cases  
108 for these paths. Starting with November 2022 and going forward, BPA will also allocate  
109 base ETC across the Cross Cascades North E>W path by only modeling BPA's lines in the  
110 base ETC cases for this path. BPA does not allocate base ETC across any other shared  
111 flow-based paths.

112 BPA calculates Power Transfer Distribution Factors based on the entire path definition of all  
113 paths.

114 At this time BPA does not allocate transfer capabilities among multiple lines or sub-paths  
115 within a larger path or between TSPs to address forward-looking congestion management and  
116 seams coordination. (MOD-001 R3.5)

---

## 117 **V. Outages**

---

118 Outages from all TSPs that are internal or adjacent to BPA's Balancing Authority Area (BAA)  
119 can be mapped to the WECC base cases. (MOD-001 R3.6.3)

### 120 **Outage Planning**

121 Outage plans and the policy are posted to the Outage Plans website at: [Outage Coordination -  
122 Bonneville Power Administration \(bpa.gov\)](https://www.bpa.gov/outage-coordination)

### 123 **Outage Criteria for TTC Calculations**

124 BPA incorporates outages into the TTC calculations after they have been studied by BPA or  
125 provided to BPA by another TOP. Generally, BPA studies outages 10 to 16 days prior to the  
126 outage start date.

127 The duration of an outage is not a criteria by which BPA determines which outages to  
128 incorporate in its daily and monthly TTC calculations. The most conservative hourly TTC  
129 calculated for a given outage or combination of outages becomes the governing TTC for the  
130 daily calculation period. Likewise, the most conservative daily TTC for a given outage or  
131 combination of outages becomes the governing TTC for the monthly calculation period.  
132 (MOD-001 R3.6.1) (MOD-001 R.3.6.2)

---

## 133 **VI. Priorities Used to Set TTC**

---

134 BPA may update assumptions and calculate new TTCs when changes to System conditions will  
135 significantly impact those limits and may use those updated assumptions to determine new  
136 TTC values. The following hierarchy of priorities categorizes the TTC values based on the  
137 time period being calculated and the reason for the change. This prioritization may then be  
138 used to revise the path TTC for a given time period if BPA determines that more recent  
139 assumptions to calculate TTC values better reflect updated System information:

- 140 • **Real-time limit (highest priority):** The “Real-time limit” priority governs when BPA  
141 updates the assumptions of System conditions to calculate TTCs during the Real-time  
142 horizon. A change to the TTC calculation with the Real-time priority governs all other  
143 priorities. For example, if BPA receives an update that a scheduled outage will be  
144 extended by two hours early in the Real-time day, BPA may update the assumptions  
145 for the TTC calculation accordingly for the additional two hours and may use those  
146 same updated assumptions to update the TTC. If there are multiple real-time updates  
147 to assumptions for TTC calculations, the most recent TTC calculated governs.
- 148 • **Scheduling limit:** The “scheduling limit” priority may be used occasionally when the  
149 assumptions for the TTC are not governing or an actual scheduling limit has been  
150 imposed. If there is more than one scheduling limit, the lowest scheduling limit  
151 governs until a Real-time limit TTC is submitted.
- 152 • **Pre-schedule forecast:** The “pre-schedule forecast” TTC priority may be used for a  
153 path if the assumptions for the TTC calculations are updated for the pre-schedule  
154 period. For example, for TTCs calculated for flow-based paths that are derived using  
155 nomograms, if the assumptions are re-evaluated just prior to the pre-schedule day to  
156 incorporate updated data inputs, the TTC may be updated. The pre-schedule forecast  
157 TTC governs over the ‘studied’ priority.
- 158 • **Studied:** The “studied” priority is used when there are outages where a study report  
159 has been issued, including those provided by other TOPs. For example, if a study  
160 report is issued evaluating assumptions for line outage system conditions, the TTCs in  
161 that report govern over any lower-priority TTCs for the duration of the line outage  
162 conditions.
- 163 • **Estimated known limit:** The “estimated known limit” priority is used to establish  
164 unstudied TTCs or to define seasonal path TTCs that govern over “short-term  
165 seasonal” or “Path Rating” priorities.
- 166 • **Short-term seasonal:** The “short-term seasonal” priority is used for TTCs issued for  
167 seasonal Path Ratings. As these Ratings may be higher at certain times during the  
168 year, the short-term seasonal priority governs over the Path Rating priority. For  
169 example, if the longer-term Path Rating for a path is 7800 MW, but seasonally this  
170 Rating increases to 8000 MW, the short-term seasonal Rating of 8000 MW governs and  
171 is used to set the TTC during the season to which it applies.
- 172 • **Path Rating:** The “Path Rating” priority is used to set base TTCs using either the  
173 Rating of the paths, TTCs studied using normal conditions, TTCs calculated for the  
174 planning horizon, or all of the above. The lowest value resulting from the above  
175 calculations governs for the given time period and is used to set the TTC. For  
176 example, if under normal conditions the TTC for a path is 4410 MW, but the TTC  
177 calculated for the planning horizon is 4100 MW, the lower TTC of 4100 MW governs and  
178 is used to set the TTC for the path.
- 179 • **Informational limit (lowest priority):** The “informational limit” is used while  
180 establishing the initial setup of paths within the scheduling and reservation system.  
181 The informational limit is equal to the initial Path Rating of the path.

---

## 182 VII. Rated System Path Methodology for BPA’s Paths

---

183 This section describes how BPA implements the Rated System Path methodology for its paths.  
184 It addresses all of the requirements in MOD-029-2a.

185 **BPA's Paths**

186 The following tables list BPA's paths. BPA has a combination of 1:1 and flow-based paths, and  
 187 uses MOD-029-2a to calculate ATC for both.

188 **Table 1, BPA's 1:1 Paths**

1:1 Path Name	Direction	1:1 OASIS Path Name
Northern Intertie	(N>S)	NI_TOTL_N>S
Northern Intertie	(S>N)	NI_TOTL_S>N
West of Garrison	(E>W)	WOGARR_E>W
West of Garrison	(W>E)	WOGARR_W>E
La Grande	(W>E)	LAGR_W>E
La Grande	(E>W)	LAGR_E>W
Montana Intertie	(E>W)	MI_E>W
Reno-Alturas NW Sierra	(N>S)	RATS_N>S
Reno-Alturas NW Sierra	(S>N)	RATS_S>N
AC Intertie (NWACI)	(N>S)	AC_N>S
AC Intertie (NWACI)	(S>N)	AC_S>N
Pacific DC Intertie	(S>N)	DC_S>N
Pacific DC Intertie	(N>S)	DC_N>S
Rock Creek Wind	Gen	ROCKCK_GEN
John Day Wind	Gen	JDWIND_GEN
Satsop Injection	Gen	SATSOP_GEN

189 **Table 2, BPA's Flow-Based Paths**

Flow-based Path Name	Direction	Flow-based OASIS Path Name	Transmission Line Components	Case used for base ETC calculation
North of Hanford	(N>S)	NOHANF	Vantage-Hanford #1 500-kV; Grand Coulee-Hanford #1 500-kV; and Shultz-Wautoma #1 500-kV	Heavy load case



Flow-based Path Name	Direction	Flow-based OASIS Path Name	Transmission Line Components	Case used for base ETC calculation
North of Hanford	(S>N)	NOHANF_S>N	Hanford-Vantage #1 500-kV; Hanford-Grand Coulee #1 500-kV; and Wautoma-Shultz #1 500-kV	Heavy load case
South of Allston	(N>S)	SOALSN	<b>BPA-Owned Transmission Lines:</b> Allston-Keeler 500-kV; Lexington-Ross 230-kV; and Allston-St. Helens 115-kV; <b>Portland General Electric-Owned Transmission Lines:</b> Trojan-St. Marys 230-kV; and Trojan-Harbor-ton 230-kV; <b>PacifiCorp-Owned Transmission Lines:</b> Merwin-St. Johns 115-kV; Astoria-Seaside 115-kV; and Clatsop 230/115-kV	Heavy load case
South of Allston	(S>N)	SOALSN_S>N	<b>BPA-Owned Transmission Lines:</b> Keeler-Allston 500-kV; Ross-Lexington 230-kV; and St. Helens-Allston 115-kV; <b>Portland General Electric-Owned Transmission Lines:</b> St. Marys-Trojan 230-kV; and Harbor-ton-Trojan 230-kV; <b>PacifiCorp-Owned Transmission Lines:</b> St. Johns-Merwin 115-kV; Seaside-Astoria 115-kV; and Clatsop 230/115-kV	Heavy load case
Raver-Paul	(N>S)	RAVR_PAUL	Raver-Paul #1 500-kV <b>When Raver-Paul #1 500-kV is out of service, the following lines are monitored:</b> Raver-Paul #1 500-kV; St. Clair-South Tacoma #1 230-kV; Chehalis-Covington #1 230-kV; Frederickson-St. Clair 115-kV; and Electron Heights-Blumaer 115-kV	Heavy load case

Flow-based Path Name	Direction	Flow-based OASIS Path Name	Transmission Line Components	Case used for base ETC calculation
Cross Cascades North	(E>W)	C-CASC_N	<p><b>BPA-Owned Transmission Lines:</b>  Schultz-Raver #1, #3, &amp; #4 500-kV;  Schultz-Echo Lake #1 500-kV;  Chief Joseph-Monroe #1 500-kV;  Chief Joseph-Snohomish #3 &amp; #4 345-kV;  Rocky Reach-Maple Valley #1 345-kV;  Grand Coulee-Olympia #1 287-kV; and  Bettas Road-Covington #1 230-kV;</p> <p><b>Puget Sound Energy-Owned Transmission Line:</b>  Rocky Reach-Cascade 230-kV</p>	Heavy load case
Cross Cascades South	(E>W)	C-CACS_S	<p><b>BPA-Owned Transmission Lines:</b>  Big Eddy-Ostrander #1 500-kV;  Ashe-Marion #2 500-kV;  Buckley-Marion #1 500-kV;  Knight-Ostrander #1 500-kV;  John Day-Marion #1 500-kV;  McNary-Ross #1 345-kV;  Big Eddy-Chemawa #1 230-kV;  Big Eddy-McLoughlin #1 &amp; #2 230-kV;  Midway-North Bonneville #1 230-kV;  Jones Canyon-Santiam #1 230-kV; and  Big Eddy-Troutdale #1 230-kV</p> <p><b>PGE-Owned Transmission Line:</b>  Round Butte-Bethel 230-kV</p>	Heavy load case
West of McNary	(E>W)	WOMCNY	Coyote Springs-Slatt #1 500-kV; McNary-Ross #1 345-kV; Harvalum-Big Eddy #1 230-kV; Jones Canyon-Santiam #1 230-kV; and McNary-John Day #2 500-kV	Heavy load case
West of Slatt	(E>W)	WOSLATT	Slatt-Buckley #1 500-kV; and Slatt-John Day #1 500-kV	Heavy load case
West of John Day	(E>W)	WOJD_E>W	John Day-Big Eddy #1 500-kV; John Day-Big Eddy #2 500-kV; and John Day-Marion #1 500-kV	Heavy load case
South of Boundary	(N>S)	SBNDRY_N>S	Boundary-Bell #1 230-kV; Boundary-Bell #3 230-kV; Boundary-Usk #1 230-kV; and Boundary 230/115-kV Transformer #1	Heavy load case

Flow-based Path Name	Direction	Flow-based OASIS Path Name	Transmission Line Components	Case used for base ETC calculation
Columbia Injection	(N>S)	CLMBIA_N>S	<b>BPA-Owned Transmission Lines:</b> Columbia-Grand Coulee #1 230-kV; Columbia-Grand Coulee #3 230-kV; Columbia-Rocky Reach #2 230-kV; Columbia-Valhalla #1 115-kV; and Columbia-Valhalla #2 115-kV; <b>Chelan PUD-Owned Transmission Line:</b> Columbia-Rocky Reach #1 230-kV	Heavy load case
Wanapum Injection	(N>S)	WANAPM_N>S	<b>BPA-Owned Transmission Line:</b> Vantage-Midway #1 230-kV; <b>Grant PUD-Owned Transmission Line:</b> Priest Rapids-Midway #3 230-kV	Heavy load case
West of Lower Monumental	(E>W)	W_LOMO_E>W	Lower Monumental-Ashe 500-kV; Lower Monumental-Hanford 500-kV; and Lower Monumental-McNary 500-kV	Heavy load case
North of Echo Lake	(S>N)	N_ECOL_S>N	Echo Lake-Monroe-SnoKing Tap #1 500-kV; Echo Lake-Maple Valley #1 500-kV; Echo Lake-Maple Valley #2 500-kV; and Covington-Maple Valley #2 230-kV	Heavy load case
South of Custer	(N>S)	SCSTER_N>S	Custer-Monroe #1 500-kV; Custer-Monroe #2 500-kV; Custer-Bellingham #1 230-kV; and Custer-Murray #1 230-kV	Heavy load case
West of Hatwai	(E>W)	WOH_E>W	Hatwai-Lower Granite #1 500-kV; Bell-Grand Coulee #6 500-kV; Bell-Grand Coulee #3 230-kV; Bell-Grand Coulee #5 230-kV; Westside-Grand Coulee #1 230-kV; Dry Creek-Talbot 230-kV; North Lewiston-Tucannon River #1 115-kV; Devils Gap-Stratford 115-kV; Lind-Warden 115-kV; Creston-Bell #1 115-kV; and Dry Gulch-Pomeroy 69-kV	Light load case

190 BPA will select the Rated System Path Methodology if new paths are implemented, and  
191 update the appropriate table above. (MOD-001 R1)

## 192 Calculating TTC

### 193 Data and Assumptions

194 When calculating TTC for its paths, BPA uses WECC base cases that utilize data and  
195 assumptions consistent with the time period being studied. (MOD-029, R1.1) In addition to  
196 BPA's TOP area, these WECC base cases model the entire Western Interconnection.  
197 Hence, the WECC base cases include all TOP areas regardless if they are either contiguous  
198 to BPA's TOP area or are linked to BPA's TOP area by a joint operating Agreement. (MOD-  
199 029 R1.1.1.2, R1.1.1.3)

200 TOP areas contiguous with BPA's TOP area include (MOD-029 R1.1.1.2):

- 201 • Avista Corporation (AVA)
- 202 • BC Hydro (BCH)
- 203 • California Independent System Operator (CAISO)
- 204 • City of Tacoma, Department of Public Utilities, Light Division
- 205 • Eugene Water and Electric Board (EWEB)
- 206 • Idaho Power Company (IPCO)
- 207 • Los Angeles Department of Water and Power (LADWP)
- 208 • NorthWestern Energy (NWMT)
- 209 • NV Energy
- 210 • PacifiCorp (PAC)
- 211 • Pend Oreille County Public Utility District No. 1
- 212 • Portland General Electric (PGE)
- 213 • Public Utility District No. 1 of Chelan County
- 214 • Public Utility District No. 1 of Clark County
- 215 • Public Utility District No. 1 of Snohomish County
- 216 • Public Utility District No. 2 of Grant County, Washington
- 217 • PUD No. 1 of Douglas County
- 218 • Puget Sound Energy, Inc. (PSEI)
- 219 • Seattle City Light (SCL)

220 BPA uses the following data and assumptions in the WECC base cases when calculating  
221 TTCs for its paths:

222 BPA models all existing System Elements in their normal operating condition for the  
223 assumed initial conditions, up to the time horizon in which BPA begins modeling  
224 outages. (MOD-029 R1.1.2)

225 The WECC base cases include generators and phase shifters that meet the guidelines  
226 set out in the WECC Data Preparation Manual. (MOD-029 R1.1.3) (MOD-029 R1.1.4)

227 BPA uses the seasonal Load forecasts contained in the WECC base cases for each BA.  
228 (MOD-029 R1.1.5)

229 Generation and Transmission Facility additions and retirements within the WECC  
230 footprint are included in the WECC seasonal operating base cases for the season in  
231 which they are energized/de-energized, respectively. BPA engineers modify the WECC  
232 base cases to reflect the actual dates of energization/de-energization. (MOD-029  
233 R1.1.6, R1.1.7)

234 The WECC base cases include Facility Ratings as provided to WECC by the Transmission  
235 Owners and Generator Owners. (MOD-029 R1.2)

236 If Facility changes are made by BPA or another entity, then the base cases will be  
237 updated to reflect these changes with a Mid-Season update. (MOD-029 R1.1, R1.2)

238 The approved seasonal operating base cases that include the Facility changes will not  
239 be used until 0 to 16 days prior to the energization or implementation of the Facility  
240 change. (MOD-029 R1.1, R1.2)

241 For periods beyond two weeks, the WECC base cases will be updated as necessary to  
242 perform seasonal studies for the current or upcoming season in accordance with the  
243 current BPA study processes. (MOD-029 R1.1, R1.2, R2.1)

244 For all paths, except West of Garrison and Northern Intertie South to North, BPA uses  
245 the all lines in service TTC from the relevant seasonal studies when there are no  
246 studied outages to set the TTC of the path for the corresponding seasonal time  
247 periods.

248 For West of Garrison, for the seasons or time periods in which the seasonal studies  
249 have not been completed, the most recent year's seasonal study results will be used  
250 for setting the TTC for the path.

251 For Northern Intertie South to North, for the seasons or time periods in which the  
252 seasonal studies have not been completed, the most recent year's seasonal study  
253 results will be used for setting the TTC. BPA uses the minimum TTC from the relevant  
254 seasonal studies to set the TTC of the path for periods from the next day and  
255 beyond. For the Real-time horizon, when there are no studied outages, BPA uses the  
256 maximum TTC from the relevant seasonal studies to set the TTC of the path.

257 BPA models Special Protection Systems (BPA uses the term Remedial Action Schemes  
258 or RAS) that currently exist or are projected for implementation within the studied  
259 time horizon. (MOD-029 R1.1.8)

260 The WECC base cases include all series compensation for each line at the expected  
261 operating level. (MOD-029 R1.1.9)

262 BPA uses no other modeling requirements for calculating TTC in addition to those  
263 specified in this document. (MOD-029 R1.1.10)

#### 264 **Process to Determine TTC**

265 BPA adjusts generation and Load levels within the WECC power-flow base cases to  
266 determine the TTC that can be simulated for each of its paths, while at the same time  
267 satisfying all operations planning criteria contingencies, as follows:

268 BPA studies single and multiple contingencies that are relevant to the path being studied.  
269 (MOD-029 R2.1)

270 When modeling normal conditions, BPA models all Transmission Elements in BPA’s BAA and  
271 adjacent BAAs at or below 100 percent of their continuous Rating. (MOD-029 R2.1.1)

272 BPA models contingencies as per the current version of “RC West System Operating Limits  
273 Methodology for the Operations Horizon” (RC West SOL Methodology) posted on RC West’s  
274 website. (MOD-029 R2.1.2)

275 When modeling contingencies, BPA determines TTCs by stressing the system until flows  
276 exceed emergency Facility Ratings or voltages fall outside emergency system voltage  
277 limits (i.e., the post-Contingency state). If a facility does not have an emergency Facility  
278 Rating, the normal Facility Rating is used. If there is no emergency system voltage limit,  
279 the normal system voltage limit is used. (MOD-029 R2.1.2) By meeting the criteria in the  
280 RC West SOL Methodology, uncontrolled separation should not occur. (MOD-029 R2.1.3)

281 BPA’s paths listed below are bi-directional and have studied TTCs in both the prevailing  
282 and non-prevailing direction of flow. (MOD-029 R2.2)

283       • Northern Intertie  
284       • West of Garrison  
285       • La Grande  
286       • Reno-Alturas NW Sierra  
287       • AC Intertie (NWACI)  
288       • Pacific DC Intertie  
289       • North of Hanford  
290       • South of Allston

291 All of BPA’s other paths are one directional, in the prevailing direction of flow, and have  
292 studied TTCs that are established for the prevailing direction of flow. If TTC values for  
293 the non-prevailing direction of flow were needed for these paths, BPA would determine  
294 these TTC values in accordance with the sub-requirements listed in MOD-029 R2, including  
295 MOD-029 R2.2.

296 For paths where TTC varies due to simultaneous interaction with one or more other paths,  
297 BPA develops a nomogram, represented either by an equation or its graphical  
298 representation, describing the interaction of the paths and the resulting TTC under  
299 specified conditions. BPA then calculates a value, based on that nomogram and  
300 forecasted System conditions for the time period studied, to develop its TTC values for  
301 the affected paths. (MOD-029 R2.4)

302 BPA or the adjacent path TOP identifies when the new or increased TTC for a path being  
303 studied by BPA or the adjacent path TOP has an adverse impact on the TTC value of  
304 another existing path by modeling the flow on the path being studied at its proposed new  
305 TTC level, while simultaneously modeling the flow on the existing path at its TTC level. In  
306 doing so, BPA or the adjacent path TOP honors the reliability criteria described above.  
307 BPA or the adjacent path TOP includes the resolution of this adverse impact in its study  
308 report for the path. (MOD-029 R2.5)

309 BPA has Transmission Ownership Agreements where multiple ownerships of Transmission  
310 rights exist on a path. TTC for the affected paths is allocated according to contractual  
311 ownership rights. (MOD-029 R2.6)

312 The ratings for BPA's paths whose ratings were established, known, and used in operation  
313 since January 1, 1994, have been re-established using updated methods. BPA studies its  
314 paths, with the exception of LaGrande, on a periodic basis and reconfirms the rating of  
315 each path based on these studies. These ratings are then used to establish the TTC for  
316 the path.

317 For the LaGrande path, BPA uses the Accepted Rating of the path as defined in the WECC  
318 Path Rating Catalog. BPA's LaGrande path is part of the NW-Idaho path (WECC Path  
319 14). The rating of Path 14 was reconfirmed through an updated study in 2010 when the  
320 path definition had to be modified due to the addition of the Hemingway Substation by  
321 PAC and Idaho Power.

322 BPA creates a study report that describes the TTC applicable to the outages during the  
323 studied time period and includes the limiting Contingencies and the limiting cause for the  
324 calculated TTC. The RC West SOL Methodology document defines the steps taken and  
325 assumptions BPA used to determine TTC for each path. BPA creates a study report for  
326 each study it performs. The study report relies on the basic assumptions included in RC  
327 West SOL methodology and identifies any changes to those basic assumptions. (MOD-029  
328 R2.8)

329 Information regarding TTCs is shared electronically between the appropriate BPA  
330 organizations within seven calendar days of the finalization of the study report for the TTCs.  
331 BPA sends a notice to all TSPs for the paths listed in Table 1 where there are multiple TSPs  
332 *prior* to limitations in TTCs. (MOD-029 R4)

333 These notices are called Notices of Planned Path Limitation. Where BPA has performed a  
334 study, the notice states that the TTC study report is available to TSPs for the specific path  
335 within seven calendar days upon request to [nercatcstandards@bpa.gov](mailto:nercatcstandards@bpa.gov) with **TTC Study**  
336 **Report Request** in the subject line. Use the **TTC Study Report Request Form** found on BPA's  
337 ATC Methodology website to submit the request.

338 A path for which BPA does not perform studies to determine the most current value of TTC is  
339 Reno - Alturas NW Sierra (RATS). For RATS, NV Energy determines TTC. The TTC is provided  
340 to BPA and BPA then sends a Notice of Planned Path Limitation. (MOD-029 R3)

## 341 **Calculating Firm Transmission Service for Paths**

### 342 **Calculating Firm Existing Transmission Commitments (ETC<sub>F</sub>)**

343 When calculating ETC<sub>F</sub> for all time periods for its paths, BPA uses the following algorithm as  
344 specified in MOD-029 R5:

$$345 \text{ETC}_F = \text{NL}_F + \text{NITS}_F + \text{GF}_F + \text{PTP}_F + \text{ROR}_F + \text{OS}_F$$

346



347 **Where:**

348  $NL_F$  is the firm capacity set aside to serve peak Native Load forecast commitments for the  
349 time period being calculated, to include losses, and Native Load growth, not otherwise  
350 included in Transmission Reliability Margin or Capacity Benefit Margin.

351 BPA does not have any  $NL_F$ , and thus sets  $NL_F$  at zero for all of its paths for all time  
352 periods. All of BPA's firm Transmission obligations are captured in the  $NITS_F$ ,  $PTP_F$ ,  $GF_F$   
353 and  $ROR_F$  components of the  $ETC_F$  algorithm.

354  $NITS_F$  is the firm capacity reserved for Network Integration Transmission Service serving Load,  
355 to include losses, and Load growth, not otherwise included in Transmission Reliability Margin  
356 or Capacity Benefit Margin.

357 For BPA's 1:1 paths where  $NITS_F$  commitments exist to serve Network Load outside BPA's  
358 BAA, the firm capacity set aside for  $NITS_F$  is equal to the Load forecast, which includes  
359 losses and Load growth, minus generation outside BPA's BAA that is designated to serve  
360 that Load. For BPA's 1:1 paths where  $NITS_F$  commitments exist to serve Network Load  
361 inside BPA's BAA from a forecasted or designated network resource that impacts the path,  
362 the firm capacity set aside for  $NITS_F$  is equal to the amount the resource is  
363 forecasted/designated for.

364 For BPA's flow-based paths, BPA accounts for  $NITS_F$  obligations with a combination of base  
365 ETC and interim ETC calculations, as described further in this document.

366  $GF_F$  is the firm capacity set aside for grandfathered Transmission Service and contracts for  
367 energy and/or Transmission Service, where executed prior to the effective date of a  
368 Transmission Service Provider's Open Access Transmission Tariff or "safe harbor tariff."

369 The amount of  $GF_F$  BPA sets aside across its 1:1 paths is based on the terms of each  
370 individual contract.

371 For BPA's flow-based paths, BPA accounts for  $GF_F$  obligations with base ETC calculations,  
372 as described further in this document.

373  $PTP_F$  is the firm capacity reserved for confirmed Point-to-Point Transmission Service.

374 In BPA's calculations for 1:1 paths,  $PTP_F$  is equal to the sum of the MW Demands of  $PTP_F$   
375 reservations or schedules.

376 For BPA's flow-based paths, BPA accounts for  $PTP_F$  obligations with a combination of base  
377 ETC and interim ETC calculations, as described further in this document.

378 For Redirects from conditional short-term firm parent reservations, BPA's ETC accounts  
379 for the parent reservation until the Redirect is confirmed on OASIS. Once the Redirect is  
380 confirmed, BPA's ETC only accounts for the Redirect.

381 For Redirects from long-term firm parent reservations or unconditional short-term firm  
382 parent reservations, BPA's ETC accounts for both the parent reservation and the Redirect  
383 reservation until the Redirect itself is unconditional. Once the Redirect is unconditional,  
384 BPA's ETC only accounts for the Redirect.



385 In some cases, BPA has PTP<sub>F</sub> contracts that give customers the right to schedule between  
386 multiple Points of Receipt (PORs) and Points of Delivery (PODs). However, the customer  
387 can only schedule up to the MW amount specified in their contract. Multiple reservations  
388 are created for these special cases to allow BPA to model each POR-to-POD combination.  
389 The amount set aside for these cases does not exceed the total PTP<sub>F</sub> rights specified in  
390 the contracts.

391 **ROR<sub>F</sub>** is the firm capacity reserved for roll-over rights for contracts granting Transmission  
392 Customers the right of first refusal to take or continue to take Transmission Service when the  
393 Transmission Customer's Transmission Service contract expires or is eligible for renewal.

394 BPA assumes that all of its Transmission Service Agreements eligible to roll-over in the  
395 future will be rolled over. If a Transmission Customer chooses not to exercise its roll-over  
396 rights by the required deadline, BPA no longer holds out capacity for roll-over rights for  
397 that Transmission Customer.

398 **OS<sub>F</sub>** is the firm capacity reserved for any other service(s), contract(s), or agreement(s) not  
399 specified above using Firm Transmission Service as specified in the ATCID.

400 BPA has no OS<sub>F</sub> and thus sets OS<sub>F</sub> at zero for all of its paths for all time periods. All of  
401 BPA's firm Transmission obligations are captured in the NITS<sub>F</sub>, PTP<sub>F</sub>, GF<sub>F</sub> and ROR<sub>F</sub>  
402 components of the ETC<sub>F</sub> algorithm.

403 Although BPA uses the above algorithm to calculate ETC<sub>F</sub> for all of its paths, BPA's ETC<sub>F</sub>  
404 calculation methodology differs between its 1:1 and flow-based paths. For 1:1 paths, BPA  
405 calculates ETC<sub>F</sub> by assuming that 1 MW of reserved firm capacity equals 1 MW of ETC<sub>F</sub> across  
406 that path. The POR/POD combinations for 1:1 ATC paths that impact ETC<sub>F</sub> can be found under  
407 the Transmission Availability section of BPA's website. For the flow-based paths, BPA  
408 calculates ETC<sub>F</sub> by summing the base ETC from power-flow ETC studies with interim ETC<sub>F</sub>  
409 calculated using PTFDs.

## 410 **Determining base ETC for Flow-Based Paths**

### 411 **Use of WECC Base Cases to Determine Base ETC**

412 BPA uses the WECC seasonal base cases and modifies them to calculate the base ETC  
413 for its flow-based paths. BPA refers to these base cases as ETC Cases.

### 414 **Determining Base ETC for Heavy Load Base Cases**

415 BPA creates monthly heavy load ETC Cases to calculate base ETC values. BPA's ETC  
416 cases are produced using a power flow model that computes how much power will  
417 flow over each flow-based path for the assumed Load and generation levels for each  
418 time period studied. Counterflows are inherently modeled in these base cases.

419 BPA uses the following assumptions to create heavy load ETC Cases for its base ETC  
420 calculations:

421 **System topology:** Normal operating conditions are used. BPA uses the WECC Winter  
422 seasonal case for its November through March ETC base cases, the WECC Spring  
423 seasonal case for its April and May ETC base cases, and the WECC Summer seasonal  
424 case for its June through October ETC base cases.

425 **Load:** BPA uses loads contained in the WECC seasonal base cases for the time periods  
426 being studied, along with any updates to those loads BPA may have made after the  
427 WECC base cases were received from WECC.

428 • **NITS<sub>F</sub>, PTP<sub>F</sub> and GF<sub>F</sub>:** BPA assumes a 1-in-2 year monthly heavy load forecast in all  
429 its monthly ETC cases

430 **Generation:** For the generators in BPA’s Balancing Authority or directly  
431 interconnected to BPA, BPA uses the following generation assumptions:

432 **FCRPS:** For the FCRPS resources serving NITS<sub>F</sub>, PTP<sub>F</sub>, and GF<sub>F</sub> Long-Term Reservations,  
433 generation levels are set using a multiple-step process. For all time periods studied,  
434 BPA uses the following process:

435 • The Columbia Generating Station is assumed to be on-line at full Load in the ETC  
436 cases. Generation levels at the Libby, Hungry Horse, Dworshak, and Albeni Falls  
437 projects are set based on the requirements set forth in the 2000 Biological  
438 Opinion. The generation levels at the Willamette Valley projects<sup>4</sup> are set at a  
439 monthly fleet-aggregate lower 10th percentile of Heavy Load Hour block  
440 generation from the planning period of record and adjusted as needed to  
441 accurately reflect operations that BPA knows are in place. **Nameplate Adjusted**  
442 **Method:** When creating heavy load ETC Cases, generation levels for all other  
443 federal hydro projects<sup>5</sup> are set by first determining the nameplate for each project  
444 and then adjusting such nameplates by outages forecasted for the particular  
445 plants. Next in the month of August, the Lower Snake plants (Lower Granite,  
446 Lower Monumental, Little Goose, and Ice Harbor) are capped at the observed  
447 project outflow over the past ten Augusts. Then multiple generation scenarios are  
448 modelled by stressing one of three different “zones” of Federal hydro resources to  
449 the nameplate adjusted generation levels described above and scales the  
450 generation at the remaining Federal hydro projects to match the sum of the  
451 demands for all contracts that call out non-specific Federal hydroelectric projects  
452 as PORs after adjusting these demands for the portion served by Columbia  
453 Generating Station, Libby, Hungry Horse, Dworshak, Albeni Falls, and the  
454 Willamette Valley projects. The Federal PTP demands at each project are then  
455 added to this result to obtain the final assumed generation level for each Federal  
456 hydro project.

457 **Non-Federal Thermal Generators:** Non-federal thermal generators associated with  
458 PTP<sub>F</sub>, GF<sub>F</sub> and NITS<sub>F</sub> Transmission Service for BPA’s area and all adjacent TSP areas are  
459 set at up to the contract Demand.

---

<sup>4</sup> Willamette Valley projects include: Big Cliff, Cougar, Detroit, Dexter, Foster, Green Peter, Hills Creek, Lookout Point, and Lost Creek.

<sup>5</sup> Federal hydro projects include: Grand Coulee, Chief Joseph, Lower Granite, Lower Monumental, Little Goose, Ice Harbor, McNary, John Day, The Dalles, Bonneville.

- 460 **Wind Generators:**
- 461 • **PTP<sub>F</sub>:** Wind generators associated with PTP<sub>F</sub> Long-Term Reservations are set at
- 462 the following depending on the scenarios being run:
- 463 ○ Modeled on at 100 percent of the contract demand for the wind
- 464 generator; or
- 465 ○ Modeled off
- 466 • **NITS<sub>F</sub>:** The flow-based path impacts of wind generators identified as
- 467 designated network resources in NITS<sub>F</sub> contracts or in the NT Resources
- 468 Memorandum of Agreement in BPA’s area are determined on a flow-based
- 469 path-by-flow-based path basis and set at the greater of the following:
- 470 ○ The wind generators modeled on at the designated amount of the wind
- 471 generators; or,
- 472 ○ The wind generators modeled off and replaced by increasing the FCRPS
- 473 generation level by the designated amount of the wind generators using
- 474 the Nameplate Adjusted Method for all ETC cases described above.
- 475 Wind generators designated as network resources in NITS<sub>F</sub> contracts for all
- 476 adjacent TSPs are modeled up to the designated amount.
- 477 • **GF<sub>F</sub>:** BPA and all of BPA’s adjacent TSPs have no GF<sub>F</sub> contracts for wind
- 478 generators.

479 **Behind the Meter Generators:** Non-federal resources that do not require

480 Transmission Service over the FCRTS and that are behind the meter are set up to

481 levels used in BPA’s process for power system planning studies.

482 **Mid-Columbia Hydro Projects:** Generation levels at the non-federal Mid-Columbia

483 hydro projects are set up to 90 percent of their historical output by season.

484 When creating heavy load ETC cases, if there is more generation than load plus

485 committed exports in the base case, BPA reduces all excess generation pro rata,

486 except for the stressed FCRPS zone. The generation reduction is done to bring

487 generation and load into balance in order to solve the power flow model.

488 When creating heavy load ETC cases, if there is more load and committed exports than

489 generation in the ETC base case, BPA reduces exports on the COI and Pacific DC

490 Intertie in the ETC base case. This is done to solve the power flow model.

#### 491 **Sensitivity Studies for Heavy Load Base Cases**

492 In calculating its base ETC values, BPA runs ETC case scenarios for three different

493 sensitivities: the Canadian Entitlement Return (CER) obligation modeled on or off,

494 wind resources designated to serve PTP<sub>F</sub> and NITS<sub>F</sub> on or off, and stressing the three

495 different zones of the FCRPS.

496 For the FCRPS scenarios, the three “zones” that are stressed individually in the

497 scenarios are made up of the following projects: (i) Upper Columbia zone includes

498 Grand Coulee and Chief Joseph; (ii) Lower Snake zone includes Lower Monumental,

499 Lower Granite, Little Goose, and Ice Harbor; and (iii) Lower Columbia zone includes

500 McNary, John Day, The Dalles and Bonneville.

501 For the CER Scenarios, BPA models the FCRPS generators delivering or not delivering  
502 energy to Canada in the amount specified in the Canadian Entitlement Agreement.

503 In the CER on scenarios, BPA models the exports to Canada at the Canadian  
504 Entitlement Agreement contract level. The FCRPS generation is modeled using the  
505 Nameplate Adjusted Method.

506 In the CER off scenarios, BPA models imports from Canada at the contract rights that  
507 customers have across the Northern Intertie N>S. The FCRPS generation is also  
508 modeled using the Nameplate Adjusted Method.

509 For the wind resource scenarios, see above for a description of the base ETC  
510 assumptions for wind generators serving  $PTP_F$  and  $NITS_F$ .

511 Therefore, in its heavy load base ETC sensitivity analysis, BPA models the following 6  
512 scenarios:

- 513 1. Wind modeled off/Upper Columbia stressed
- 514 2. Wind modeled off/Lower Snake stressed
- 515 3. Wind modeled off/Lower Columbia stressed
- 516 4. Wind modeled on/Upper Columbia stressed
- 517 5. Wind modeled on/Lower Snake stressed
- 518 6. Wind modeled on/Lower Columbia stressed

519 All scenarios are run with CER modeled on and off for all months.

520 BPA uses the highest base ETC value calculated from these scenarios in its firm ATC  
521 calculations across the flow-based paths. BPA uses the lowest base ETC value from  
522 these scenarios in its non-firm ATC calculations across the flow-based paths.

523 **Determining Base ETC and Sensitivities for Light Load Base Cases**

524 BPA uses the WECC Winter seasonal light load case as the starting point for its Winter  
525 seasonal light load ETC base case. The ETC from this case is used as the base ETC for  
526 the months of November through March.

527 BPA uses the WECC Summer seasonal light load case as the starting point for its  
528 Summer light load ETC base case. The ETC from the Summer case is used as the base  
529 ETC for the months of June through October.

530 If a WECC Spring seasonal light load case is available, BPA uses that case as the  
531 starting point for its Spring seasonal light load ETC base case. The ETC from this case  
532 is used as the base ETC for the months of April and May. If the WECC Spring seasonal  
533 light load case is not available, the higher of the base ETCs from either the Winter or  
534 Summer case are used as the base ETC for April and May.

535 BPA uses the following assumptions in light load ETC base cases:

- 536 a. System topology: Normal operating conditions are used.

- 537           b. Loads: Loads from the WECC light load cases are used. Beginning with the  
538           Winter 2022 seasonal case and for Montana loads only, BPA compares the loads  
539           in the WECC seasonal light load case with the seasonal light loads supplied by  
540           Montana Power, and uses the lowest of the two values in order to properly  
541           stress the light load case.
- 542           c. Generation: BPA uses generation assumptions from historical data. Canadian  
543           Entitlement is modeled as delivering energy to Canada in the amount specified  
544           in the Canadian Entitlement Agreement.

545           There are two sensitivity studies performed for the light load ETC base cases:

- 546           a. Federal generation east of the path is increased, and a corresponding amount  
547           of federal generation west of the path is reduced
- 548           b. Federal generation east of the path is reduced, and a corresponding amount of  
549           federal generation west of the path is increased

550           BPA uses the highest base ETC value calculated from these scenarios in its firm ATC  
551           calculations across the flow-based paths where light load cases are utilized. BPA uses  
552           the lowest base ETC value from these scenarios in its non-firm ATC calculations across  
553           the flow-based paths where light load cases are utilized.

#### 554           **Calculating Interim ETC<sub>F</sub> for Flow-based Paths**

555           To calculate the impacts for all NITS<sub>F</sub> and PTP<sub>F</sub> reservations that were not modeled in the  
556           base ETC cases, BPA uses PTDF analysis on the demand in each reservation. PTDF analysis  
557           is the fraction of energy (expressed as a percentage or as a decimal) that will flow across  
558           BPA's monitored flow-based paths as that energy is injected at a POR (or source) relative  
559           to a slack bus, and withdrawn at a POD (or sink) relative to a slack bus, for each flow-  
560           based path.

561           PTDF impacts are calculated as per BPA's Transmission Service Requests Evaluation  
562           business practice. If a reservation's impact on a flow-based path is determined to be *de*  
563           *minimis* per the Transmission Service Requests Evaluation business practice, then BPA  
564           deems the impact of the reservation to be zero when calculating ETC<sub>F</sub> used in the ATC<sub>F</sub>  
565           calculation.

566           The sum of these positive impacts is referred to as the interim ETC<sub>F</sub> value, and is added to  
567           the base ETC values to produce a final ETC<sub>F</sub> value for each time period for each flow-  
568           based path.

#### 569           **Outages in PTDF Calculations**

570           BPA calculates PTDFs by adjusting the WECC base cases to include transmission  
571           outages in BPA's outage system for BPA's area and any adjacent TSP areas.  
572           Transmission outages for Transmission Lines, sections of Transmission Lines,  
573           transformers and taps are used to set branches as *open* in the appropriate base  
574           case for the hour being calculated.

575           BPA has no executed coordination Agreements with other TSPs. (MOD-001 R3.6)

576 When the Raver-Paul 500-kV line is out of service, the PTDFs that BPA calculates and  
577 uses for the Raver-Paul path are based on the monitored lines for this path that are  
578 outlined in Table 2. This allows BPA to properly manage the Raver-Paul path in this  
579 outage situation.

## 580 **Outage Criteria in ETC Calculations**

581 BPA uses the outage planning timeline described in the “Outages” section. The  
582 following criteria determine which outages are incorporated into BPA’s hourly, daily  
583 and monthly ETC calculations: (MOD-001 R3.6)

### 584 **Hourly ETC Calculations**

585 For its hourly ETC calculations, BPA uses hourly PTDFs published at least once per  
586 day.

### 587 **Daily ETC Calculations**

588 For its daily ETC calculations, BPA uses the most recent PTDFs published for the  
589 hour ending 11 of each day, since hour ending 11 tends to have the highest  
590 coincidence of outages. Therefore all Transmission outages scheduled to occur  
591 during the hour ending 11, regardless of the duration of the outage, impact daily  
592 ETC calculations. (MOD-001 R3.6.1)

593 BPA includes Transmission outages in daily ETC calculations beyond the 10- to 16-  
594 day planned outage study period if the outage is officially scheduled in BPA’s  
595 outage system.

### 596 **Monthly ETC Calculations**

597 For its monthly ETC calculations, BPA uses the most recent daily PTDFs published  
598 for the first Tuesday of that month. BPA includes Transmission outages in monthly  
599 ETC calculations beyond the 10- to 16-day planned outage study period if the  
600 outage is officially scheduled in BPA’s outage system. (MOD-001 R3.6.2)

## 601 **Source/POR and Sink/POD Identification and Mapping**

602 In the ETC components of its flow-based path ATC calculations, BPA accounts for  
603 source and sink for Transmission Service through the following processes:

604 BPA maps the source/POR and sink/POD to the WECC base cases. In this mapping, BPA  
605 has assigned network bus points that represent the primary interface for  
606 Interconnection with specific generation projects, adjacent electrical Systems or  
607 Load-serving entities and trading hubs. Some adjacent electrical Systems have  
608 multiple Interconnection points deemed as PORs/sources or PODs/sinks. The mapping  
609 of these points is published in the Transmission Service Contract Points list on BPA’s  
610 OASIS homepage.

611 BPA calculates weighted PTDFs for Sources/PORs as follows:

- 612 1. The PTDF weighting for the FCRPS/BPA Power PTDF varies by time period and path  
613 based on stress scenarios. The PTDF weighting is derived from generation  
614 forecasts of the federal resources, for calculations for the next hour through



615 approximately two weeks. Beyond this time frame, BPA derives the weighting of  
 616 the PTDF by applying the generation dispatch determined in the ETC Cases.  
 617 2. BPA derives the PTDF weighting for the Mid-Columbia bus point by applying the  
 618 generation dispatch determined in the ETC Cases.  
 619 3. BPA has grouped the generators in its adjacent BAAs based on the primary  
 620 interface between each BAA and the generation projects within that BAA  
 621 (excluding some remote generators that are scheduled via NERC e-Tag). These  
 622 groupings are assigned weighted PTDFs that represent how the generators  
 623 participate in the group and are used to evaluate transactions within and between  
 624 adjacent BAAs that do not include BPAT. BPA derives the PTDF weightings for  
 625 these points from BAA-provided generation estimates or by applying the generation  
 626 dispatch determined in the ETC Cases if generation estimates are not available. In  
 627 the ETC Cases, these generators are modeled up to the long-term firm  
 628 Transmission rights associated with the generators.

629 BPA calculates weighted PTDFs for Sinks/PODs as follows:

- 630 1. BPA has weighted PTDFs for loads in its adjacent BAAs based on the primary  
 631 interface between each BAA and the load within that BAA. The weighting is based  
 632 on how the load is distributed in the BAA.
- 633 2. BPA calculates a weighted PTDF to account for unscheduled Network Integration  
 634 Transmission Service loads in BPA's BAA that are served from the FCRPS. The  
 635 weighting is based on the individual load forecasts for the time period being  
 636 calculated.
- 637 3. BPA calculates a weighted load for all of the BPA Power Services customers that  
 638 are served via Network Integration Transmission Service agreements. The  
 639 weighting is based on the individual load forecasts for the time period being  
 640 calculated.
- 641 4. BPA calculates a weighted load for PNGC Power, which is a Joint Operating Entity  
 642 made up of several cooperative utilities. The weighting is based on the individual  
 643 load forecasts for the time period being calculated.

644 BPA calculates one weighted PTDF that applies to the following Source/POR and  
 645 Sink/POD:

- 646 1. BPA calculates a weighed PTDF for the Western Energy Imbalance Market. This  
 647 weighting is based on the percentage of Automatic Generation Control response  
 648 (which could be zero) carried by each plant in the FCRPS.

#### 649 **Calculating Firm Available Transfer Capability (ATC<sub>F</sub>)**

650 When calculating ATC<sub>F</sub> for its paths for all time periods, BPA uses the following algorithm  
 651 (MOD-029 R7):

$$652 \quad \text{ATC}_F = \text{TTC} - \text{ETC}_F - \text{CBM} - \text{TRM} + \text{Postbacks}_F + \text{Counterflows}_F$$

653

654 **Where:**

655  $ATC_F$  is the firm Available Transfer Capability for the ATC Path for that period.

656  $TTC$  is the Total Transfer Capability of the ATC Path for that period.

657  $ETC_F$  is the sum of existing firm commitments for the ATC Path during that period.

658 For  $ATC_F$  calculations for all time periods, BPA divides  $ETC_F$  into the following variables  
659 within its ATC software:

660 
$$ETC_F = LRES + SRES + LETC - SADJ/ETC \text{ Adjustments}$$

661 **Where:**

662  $LRES$  is the sum of positive impacts of BPA's Long-Term Reservations.

663  $SRES$  is the sum of positive impacts of BPA's Short-Term Reservations.

664  $LETC$  is used to ensure that the amount of  $NITS_F$ ,  $GF_F$ ,  $PTP_F$  and  $ROR_F$  capacity BPA sets  
665 aside in the  $LRES$  variable for contracts where BPA gives customers the right to schedule  
666 the capacity reserved between multiple PORs and PODs does not exceed the total capacity  
667 specified in those contracts.

668  $LETC$  is also used to align the ETC calculated in the power flow base case with additional  
669 PTDF calculations in order to balance to the standard OATI calculation. This adjustment is  
670 derived by comparing two values: a) the impacts of the confirmed  $PTP_F$ ,  $GF_F$ ,  $NITS_F$  and  
671  $ROR_F$  Long-Term Reservations derived from the base ETC Cases and b) the impacts of the  
672 same reservations calculated using PTDF Analysis for each flow-based path. The  
673 adjustment for each flow-based path is equal to the difference of these two values.  
674 Conditional firm reservations are not included in the ETC Cases and therefore are also not  
675 included in this comparison.

676  $SADJ/ETC$  Adjustments is the variable BPA uses to make adjustments to  $ETC_F$  not  
677 captured in  $LRES$  or  $SRES$ .

678 BPA applies one such adjustment to allow for deferral competitions, as required in Section  
679 17.7 of BPA's OATT. When a deferral reservation is confirmed, BPA applies an  $SADJ/ETC$   
680 Adjustment to hold out capacity for the time period deferred, starting at the latter of five  
681 months out or the service commencement date of the original reservation, to allow for a  
682 competition. At four months out, if no competition is identified, the  $SADJ/ETC$   
683 Adjustment is modified to release the capacity for the fourth month out.

684 BPA uses a  $SADJ/ETC$  Adjustment to account for a portion of the firm TRM that BPA  
685 applies on the NI S>N.

686 BPA also uses  $SADJ/ETC$  Adjustments to ensure accurate accounting of  $ETC_F$ . These  
687 adjustments may be performed to account for situations such as data modeling  
688 corrections, and are noted in the descriptions of the adjustments.

689 The following diagram illustrates how the variables in BPA's ATC software correspond to  
690 the variables in the  $ETC_F$  algorithm.



691

<b>ETC<sub>F</sub> =</b>	<b>NITS<sub>F</sub></b>	<b>+</b>	<b>GF<sub>F</sub></b>	<b>+</b>	<b>PTP<sub>F</sub></b>	<b>+</b>	<b>ROR<sub>F</sub></b>
	↓		↓		↓		↓
	<b>LRES</b>		<b>LRES</b>		<b>LRES</b>		<b>LRES</b>
	<b>+</b>				<b>+</b>		
	<b>SRES</b>				<b>SRES</b>		
	<b>+</b>		<b>+</b>		<b>+</b>		<b>+</b>
	<b>LETC</b>		<b>LETC</b>		<b>LETC</b>		<b>LETC</b>
	<b>-</b>		<b>-</b>		<b>-</b>		<b>-</b>
	<b>SADJ/ETC Adjustments</b>		<b>SADJ/ETC Adjustments</b>		<b>SADJ/ETC Adjustments</b>		<b>SADJ/ETC Adjustments</b>

692 **CBM** is the Capacity Benefit Margin for the ATC Path during that period.

693 BPA does not maintain CBM and thus sets CBM at zero for all of its paths for all time  
694 periods.

695 **TRM** is the Transmission Reliability Margin for the ATC Path during that period.

696 The description of how BPA implements TRM can be found in BPA’s TRMID, which is posted  
697 on BPAs website.

698 **Postbacks<sub>F</sub>** are changes to firm Available Transfer Capability due to a change in the use of  
699 Transmission Service for that period, as defined in Business Practices.

700 BPA automatically recalculates ETC<sub>F</sub> to account for changes to Transmission Service  
701 Requests (such as request types of Recall and Redirect and annulments). Since these  
702 types of changes to Transmission Service Requests are captured in ETC<sub>F</sub>, BPA sets  
703 Postbacks<sub>F</sub> at zero for all time periods when calculating ATC<sub>F</sub>.

704 **Counterflows<sub>F</sub>** are adjustments to firm Available Transfer Capability as determined by the  
705 Transmission Service Provider and specified in their ATCID.

706 BPA does not include confirmed Transmission reservations, expected interchange or  
707 internal flow counter to the direction of the path being calculated in its ATC<sub>F</sub> calculations.  
708 BPA’s rationale is that it does not want to offer firm ATC due to counterflow that may not  
709 be scheduled as this could lead to curtailments of Firm Transmission Service in the Real-  
710 time horizon. (MOD-001 R3.2) Therefore BPA sets Counterflows<sub>F</sub> at zero for all of its paths  
711 for all time periods.

712 For flow-based paths, counterflows are automatically modeled in the base ETC cases. In  
713 instances where the power flow study results in a negative base ETC value, BPA uses zero  
714 as the base ETC for purposes of calculating ATC<sub>F</sub>. This is done to ensure that BPA does not  
715 make capacity available as a result of counterflows that may or may not materialize in  
716 real-time.

## 717 **Calculating Non-Firm Transmission Service for BPA’s Paths**

718 BPA calculates  $ETC_{NF}$  and  $ATC_{NF}$  for each of its six non-firm Transmission products. The six  
719 non-firm products are: Secondary Network ( $NITS_{NF6}$ ), Monthly Non-Firm PTP ( $PTP_{NF5}$ ), Weekly  
720 Non-Firm PTP ( $PTP_{NF4}$ ), Daily Non-Firm PTP ( $PTP_{NF3}$ ), Hourly Non-Firm PTP ( $PTP_{NF2}$ ) and  
721 Secondary Non-Firm Hourly PTP ( $PTP_{NF1}$ ).

## 722 **Calculating Non-Firm Existing Transmission Commitments ( $ETC_{NF}$ )**

723 BPA calculates  $ETC_{NF}$  for all time periods and paths using the algorithm in MOD-029 R6:

$$724 \quad ETC_{NF} = NITS_{NF} + GF_{NF} + PTP_{NF} + OS_{NF}$$

725  $ETC_{NF}$  is calculated for each of BPA’s six non-firm Transmission products as follows:

- 726 1.  $ETC_{NF6}$ : includes the  $NITS_{NF6}$  transmission product
- 727 2.  $ETC_{NF5}$ : includes the  $NITS_{NF6}$  and  $PTP_{NF5}$  transmission products
- 728 3.  $ETC_{NF4}$ : includes the  $NITS_{NF6}$ ,  $PTP_{NF5}$  and  $PTP_{NF4}$  transmission products
- 729 4.  $ETC_{NF3}$ : includes the  $NITS_{NF6}$ ,  $PTP_{NF5}$ ,  $PTP_{NF4}$ , and  $PTP_{NF3}$  transmission products
- 730 5.  $ETC_{NF2}$ : includes the  $NITS_{NF6}$ ,  $PTP_{NF5}$ ,  $PTP_{NF4}$ ,  $PTP_{NF3}$  and  $PTP_{NF2}$  transmission products
- 731 6.  $ETC_{NF1}$ : includes the  $NITS_{NF6}$ ,  $PTP_{NF5}$ ,  $PTP_{NF4}$ ,  $PTP_{NF3}$ ,  $PTP_{NF2}$  and  $PTP_{NF1}$  transmission products

### 732 **Where:**

733  $NITS_{NF}$  is the non-firm capacity set aside for Network Integration Transmission Service serving  
734 Load (i.e., secondary service), to include losses, and Load growth not otherwise included in  
735 Transmission Reliability Margin or Capacity Benefit Margin.

736 In BPA’s calculations, this is comprised of the  $NITS_{NF6}$  Transmission product. BPA’s  $NITS_{NF6}$   
737 calculation does not include losses or Load growth, since losses and Load growth are  
738 already set aside as firm capacity in  $NITS_F$ .

739  $GF_{NF}$  is the non-firm capacity set aside for grandfathered Transmission Service and contracts  
740 for energy and/or Transmission Service, where executed prior to the effective date of a  
741 Transmission Service Provider’s Open Access Transmission Tariff or “safe harbor tariff”.

742 BPA does not have any grandfathered non-firm Transmission Service obligations and thus  
743 sets  $GF_{NF}$  at zero for all of its paths for all time periods.

744  $PTP_{NF}$  is non-firm capacity reserved for confirmed Point-to-Point Transmission Service.

745 Depending on the  $ETC_{NF}$  being calculated,  $PTP_{NF}$  will include the  $PTP_{NF5}$ ,  $PTP_{NF4}$ ,  $PTP_{NF3}$ ,  
746  $PTP_{NF2}$  and  $PTP_{NF1}$  Transmission products.

747  $OS_{NF}$  is the non-firm capacity reserved for any other service(s), contract(s), or agreement(s)  
748 not specified above using non-firm transmission service as specified in the ATCID.

749 BPA has no  $OS_{NF}$  and thus sets  $OS_{NF}$  at zero for all of its paths for all time periods.

750  $ETC_{NF}$  for 1:1 paths is calculated by assuming that 1 MW of reserved and/or scheduled capacity  
751 results in 1 MW of impact across the 1:1 path. The POR/POD combinations for 1:1 ATC paths  
752 that impact  $ETC_{NF}$  can be found under the Transmission Availability section of BPA's website.

753 When calculating  $ETC_{NF}$  for flow-based paths, BPA sums the positive impacts of reservations  
754 and/or schedules as determined by PTFD analysis, per BPA's Transmission Service Requests  
755 Evaluation business practice. The treatment of *de minimis* impacts in  $ETC_{NF}$  is covered within  
756 the Calculating Non-Firm Available Transfer Capability section below.

### 757 **Calculating Non-Firm Available Transfer Capability ( $ATC_{NF}$ )**

758 BPA calculates  $ATC_{NF}$  for its paths for two horizons: Real-time and Beyond Real-time. The  
759 Real-time horizon begins at 10 p.m. each day for the 24 hours in the next day. The Beyond  
760 Real-time horizon includes hourly for the hours after those included in the Real-time period  
761 as well as daily and monthly calculations.

762 BPA calculates  $ATC_{NF}$  for all time periods and paths using the algorithm found in MOD-029 R8:

$$763 \quad \mathbf{ATC}_{NF} = \mathbf{TTC} - \mathbf{ETC}_F - \mathbf{ETC}_{NF} - \mathbf{CBM}_S - \mathbf{TRM}_U + \mathbf{Postbacks}_{NF} + \mathbf{Counterflows}_{NF}$$

764  $ATC_{NF}$  is calculated for each of BPA's six non-firm Transmission products as follows:

$$765 \quad 1. \quad \mathbf{ATC}_{NF6} = \mathbf{TTC} - \mathbf{ETC}_F - \mathbf{ETC}_{NF6} - \mathbf{CBM}_S - \mathbf{TRM}_U + \mathbf{Postbacks}_{NF} + \mathbf{Counterflows}_{NF}$$

$$766 \quad 2. \quad \mathbf{ATC}_{NF5} = \mathbf{TTC} - \mathbf{ETC}_F - \mathbf{ETC}_{NF5} - \mathbf{CBM}_S - \mathbf{TRM}_U + \mathbf{Postbacks}_{NF} + \mathbf{Counterflows}_{NF}$$

$$767 \quad 3. \quad \mathbf{ATC}_{NF4} = \mathbf{TTC} - \mathbf{ETC}_F - \mathbf{ETC}_{NF4} - \mathbf{CBM}_S - \mathbf{TRM}_U + \mathbf{Postbacks}_{NF} + \mathbf{Counterflows}_{NF}$$

$$768 \quad 4. \quad \mathbf{ATC}_{NF3} = \mathbf{TTC} - \mathbf{ETC}_F - \mathbf{ETC}_{NF3} - \mathbf{CBM}_S - \mathbf{TRM}_U + \mathbf{Postbacks}_{NF} + \mathbf{Counterflows}_{NF}$$

$$769 \quad 5. \quad \mathbf{ATC}_{NF2} = \mathbf{TTC} - \mathbf{ETC}_F - \mathbf{ETC}_{NF2} - \mathbf{CBM}_S - \mathbf{TRM}_U + \mathbf{Postbacks}_{NF} + \mathbf{Counterflows}_{NF}$$

$$770 \quad 6. \quad \mathbf{ATC}_{NF1} = \mathbf{TTC} - \mathbf{ETC}_F - \mathbf{ETC}_{NF1} - \mathbf{CBM}_S - \mathbf{TRM}_U + \mathbf{Postbacks}_{NF} + \mathbf{Counterflows}_{NF}$$

771 Table 3 outlines the differences in how the  $ATC_{NF}$  algorithm components are calculated  
772 between the Beyond Real-time and Real-time time horizons.

773

Table 3, ATC<sub>NF</sub> Calculation for Beyond Real-Time and Real-Time Horizons

Algorithm Component	Beyond Real-time	Real-time
TTC	As described in TTC section in the ATCID	Same
ETC <sub>F</sub>	Calculated using reservations and base ETC cases for flow-based paths <ul style="list-style-type: none"> <li>• <i>De minimis</i> impacts are treated as zero in ETC<sub>F</sub></li> </ul>	Calculated using schedules <ul style="list-style-type: none"> <li>• <i>De minimis</i> impacts are included in ETC<sub>F</sub></li> </ul>
ETC <sub>NF</sub>	Calculated using reservations <ul style="list-style-type: none"> <li>• <i>De minimis</i> impacts are treated as zero in ETC<sub>NF</sub></li> </ul>	Calculated using reservations until scheduled, then calculated using schedules <ul style="list-style-type: none"> <li>• <i>De minimis</i> impacts are included in ETC<sub>NF</sub> for both reservations and schedules</li> </ul>
CBM <sub>S</sub>	N/A	N/A
TRM <sub>U</sub>	As described in the TRMID	Same
Postback <sub>SNF</sub>	Zero since ETC <sub>NF</sub> is recalculated to capture changes to the Transmission Service Requests	Zero since ETC <sub>NF</sub> is recalculated to capture changes to the Transmission Service Requests and/or schedules, with the exception of AC N>S
Counterflows <sub>NF</sub>	Included with schedules	Same

775 **Where:**

776 ATC<sub>NF</sub> is the non-firm Available Transfer Capability for the ATC Path for that period.

777 BPA calculates six ATC<sub>NF</sub> values as described above.

778 TTC is the Total Transfer Capability of the ATC Path for that period.

779 ETC<sub>F</sub> is the sum of existing firm commitments for the ATC Path during that period.

780 The section below outlines how BPA calculates ETC<sub>F</sub> for all of its paths for the beyond  
781 Real-time and the Real-time horizons.

### 782 ETC<sub>F</sub> for the Beyond Real-Time Horizon

783 Reservations, and base ETC cases for flow-based paths, are used to calculate ETC<sub>F</sub> for the  
784 Beyond Real-time horizon. When calculating ETC<sub>F</sub> for this horizon, *de minimis* impacts of  
785 reservations across flow-based paths are deemed to be zero.

786 For ATC<sub>NF</sub> calculations for the beyond Real-time horizon, BPA utilizes the following  
787 variables within its ATC software to calculate ETC<sub>F</sub>:

788  $ETC_F = LRES + SRES - SADJ/ETC \text{ Adjustments} + NFETC$

789

790 **Where:**

791 **LRES** is the sum of positive impacts of BPA’s Long-Term Reservations.

792 **SRES** is the sum of positive impacts of BPA’s Short-Term Reservations.

793 **SADJ/ETC Adjustments** is the variable used to make adjustments to  $ETC_F$  not captured  
794 in LRES or SRES.

795 BPA applies one such adjustment to allow for deferral competitions, as required in  
796 Section 17.7 of BPA’s OATT. When a deferral reservation is confirmed, BPA applies a  
797 SADJ/ETC Adjustment to hold out capacity for the time period deferred, starting at  
798 the latter of five months out or the service commencement date of the original  
799 reservation, to allow for a competition. At four months out, if no competition is  
800 identified, the SADJ/ETC Adjustment is modified to add back capacity for the fourth  
801 month out.

802 BPA uses SADJ/ETC Adjustments to ensure accurate accounting of  $ETC_F$ . These  
803 adjustments may be performed to account for situations such as data modeling  
804 corrections, and are noted in the descriptions of the adjustments.

805 **NFETC** is used to ensure that the amount of  $NITS_F$ ,  $GF_F$ ,  $PTP_F$  and  $ROR_F$  capacity BPA  
806 sets aside in the LRES variable for contracts where BPA gives customers the right to  
807 schedule the capacity reserved between multiple PORs and PODs does not exceed the  
808 total capacity specified in those contracts.

809 **NFETC** is also used to align the ETC calculated in the power flow base case along with  
810 additional PTDF calculations in order to balance to the standard OATI calculation.

811 This adjustment is derived by comparing two values: a) the impacts of the  $PTP_F$ ,  $GF_F$   
812 and  $NITS_F$  Long-Term Reservations derived from the base ETC Cases and b) the impacts  
813 of the same reservations calculated using PTDF Analysis for each flow-based path. The  
814 adjustment for each flow-based path is equal to the difference of these two values.  
815 Conditional firm reservations are not included in the ETC Cases and therefore are also  
816 not included in this comparison.

817 The following diagram illustrates how the variables in BPA’s ATC software correspond  
818 to the variables in the  $ETC_F$  algorithm for the Beyond Real-time horizon.

$ETC_F =$	$NITS_F$	+	$GF_F$	+	$PTP_F$	+	$ROR_F$
	↓		↓		↓		↓
	<b>LRES</b>		<b>LRES</b>		<b>LRES</b>		<b>LRES</b>
	+				+		
	<b>SRES</b>				<b>SRES</b>		
	+		+		+		+
	<b>NFETC</b>		<b>NFETC</b>		<b>NFETC</b>		<b>NFETC</b>
	-		-		-		-
	<b>SADJ/ETC Adjustments</b>		<b>SADJ/ETC Adjustments</b>		<b>SADJ/ETC Adjustments</b>		<b>SADJ/ETC Adjustments</b>

819 **ETC<sub>F</sub> for the Real-Time Horizon**

820 For ATC<sub>NF</sub> calculations for the Real-time horizon, BPA divides ETC<sub>F</sub> into the following  
 821 variables within its ATC software:

822 
$$\text{ETC}_F = \text{SCH}^+_7 + \text{ASC}^+_7 + \text{RADJ/ETC Adjustment}$$

823 Schedules are used to calculate ETC<sub>F</sub> for the Real-time horizon. When calculating ETC<sub>F</sub> for  
 824 this horizon, *de minimis* impacts of schedules across flow-based paths are included in  
 825 ETC<sub>F</sub>.

826 **Where:**

827 **SCH<sup>+</sup><sub>7</sub>** is the sum of the positive impacts of schedules that reference confirmed NITS<sub>F</sub>,  
 828 GF<sub>F</sub> and PTP<sub>F</sub> reservations for the ATC Path for that period. The energy profile of the  
 829 schedule is used except for the schedule types of Dynamic, Capacity and Pseudo-tie.

830 **ASC<sup>+</sup><sub>7</sub>** is the sum of the positive impacts of dynamic schedules that reference  
 831 confirmed NITS<sub>F</sub>, GF<sub>F</sub> and PTP<sub>F</sub> reservations for the ATC Path for that period. The  
 832 transmission profile of the schedule is used for the schedule types of Dynamic,  
 833 Capacity and Pseudo-tie.

834 **RADJ/ETC Adjustment:** BPA uses RADJ/ETC adjustments to ensure accurate  
 835 accounting of ETC<sub>F</sub>. These adjustments may be performed to account for situations  
 836 such as data modeling corrections.

837 The following diagram illustrates how the variables in BPA’s ATC software correspond  
 838 to the variables in the ETC<sub>F</sub> algorithm for the Real-time horizon. ROR<sub>F</sub> is not included  
 839 in ETC<sub>F</sub> for the Real-time horizon because ROR<sub>F</sub> is not relevant for the Real-time  
 840 horizon.

<b>ETC<sub>F</sub> =</b>	<b>NITS<sub>F</sub></b>	<b>+</b>	<b>GF<sub>F</sub></b>	<b>+</b>	<b>PTP<sub>F</sub></b>
	↓		↓		↓
	<b>SCH<sup>+</sup><sub>7</sub></b>		<b>SCH<sup>+</sup><sub>7</sub></b>		<b>SCH<sup>+</sup><sub>7</sub></b>
	<b>+</b>		<b>+</b>		<b>+</b>
	<b>ASC<sup>+</sup><sub>7</sub></b>		<b>ASC<sup>+</sup><sub>7</sub></b>		<b>ASC<sup>+</sup><sub>7</sub></b>
	<b>+</b>		<b>+</b>		<b>+</b>
	<b>RADJ/ETC Adjustment</b>		<b>RADJ/ETC Adjustment</b>		<b>RADJ/ETC Adjustment</b>

841 **ETC<sub>NF</sub>** is the sum of existing non-firm commitments for the ATC Path during that period.

842 The section below outlines how BPA calculates ETC<sub>NF</sub> for all of its paths for the beyond  
 843 Real-time and the Real-time horizons.

844 **ETC<sub>NF</sub> for the Beyond Real-Time Horizon**

845 For ATC<sub>NF</sub> calculations for the beyond Real-time horizon, ETC<sub>NF</sub> is reflected as the  
 846 following variable within BPA’s ATC software:

847  $ETC_{NF} = RRES_{6,5,4,3,2,1}$

848 Reservations are used to calculate  $ETC_{NF}$  for the Beyond Real-time horizon. When  
849 calculating  $ETC_{NF}$  for this horizon, *de minimis* impacts of reservations across flow-based  
850 paths are deemed to be zero.

851 **Where:**

852  $RRES_{6,5,4,3,2,1}$  is the sum of the positive impacts of all confirmed  $NITS_{NF6}$ ,  $PTP_{NF5}$ ,  $PTP_{NF4}$ ,  
853  $PTP_{NF3}$ ,  $PTP_{NF2}$  and  $PTP_{NF1}$  reservations.

854 The following diagram illustrates how the variables in BPA's ATC software correspond  
855 to the variables in the  $ETC_{NF}$  algorithm for the Beyond Real-time horizon.

$ETC_{NF} =$	$NITS_{NF}$	+	$PTP_{NF}$
	↓		↓
	$RRES_6$		$RRES_{5,4,3,2,1}$

856  **$ETC_{NF}$  for the Real-Time Horizon**

857 For  $ATC_{NF}$  calculations in the Real-time horizon,  $ETC_{NF}$  is reflected as the following  
858 variables within BPA's ATC software:

859  $ETC_{NF} = SCH^+_{6,5,4,3,2,1} + ASC^+_{6,5,4,3,2,1}$

860 To calculate  $ETC_{NF}$  for the Real-time horizon, reservations are used until schedules are  
861 received, and then schedules are used. When calculating  $ETC_{NF}$  for this horizon, *de*  
862 *minimis* impacts across flow-based paths are included in  $ETC_{NF}$ , regardless of whether the  
863 reservation or schedule is being used in the calculation.

864 **Where:**

865  $SCH^+_{6,5,4,3,2,1}$  is the sum of the positive impacts of schedules referenced to confirmed  
866  $NITS_{NF6}$ ,  $PTP_{NF5}$ ,  $PTP_{NF4}$ ,  $PTP_{NF3}$ ,  $PTP_{NF2}$  and  $PTP_{NF1}$  reservations, plus the sum of the  
867 positive impacts of pending and confirmed  $NITS_{NF6}$ ,  $PTP_{NF5}$ ,  $PTP_{NF4}$ ,  $PTP_{NF3}$ ,  $PTP_{NF2}$  and  
868  $PTP_{NF1}$  reservations that have not yet been scheduled. Once these reservations are  
869 scheduled, the schedule is used for  $ETC_{NF}$ , thereby adding back the difference  
870 between the reservation and schedule amounts to  $ATC_{NF}$ . The energy profile of the  
871 schedule is used except for the schedule types of Dynamic, Capacity and Pseudo-tie.

872  $ASC^+_{6,5,4,3,2,1}$  is the sum of positive impacts of dynamic schedules referenced to  
873 confirmed  $NITS_{NF6}$ ,  $PTP_{NF5}$ ,  $PTP_{NF4}$ ,  $PTP_{NF3}$ ,  $PTP_{NF2}$  and  $PTP_{NF1}$  reservations, plus the sum of  
874 the positive impacts of pending and confirmed  $NITS_{NF6}$ ,  $PTP_{NF5}$ ,  $PTP_{NF4}$ ,  $PTP_{NF3}$ ,  $PTP_{NF2}$  and  
875  $PTP_{NF1}$  reservations that have not yet been scheduled. Once these reservations are  
876 scheduled, the schedule is used for  $ETC_{NF}$ , thereby adding back the difference  
877 between the reservation and schedule amounts to  $ATC_{NF}$ . The transmission profile of  
878 the schedule is used for the schedule types of Dynamic, Capacity and Pseudo-tie.

879 The following diagram illustrates how the variables in BPA’s ATC software correspond  
 880 to the variables in the ETC<sub>NF</sub> algorithm for the Real-time horizon.

881

<b>ETC<sub>NF</sub> =</b>	<b>NITS<sub>NF</sub></b>	<b>+</b>	<b>PTP<sub>NF</sub></b>
	↓		↓
	<b>SCH<sup>+</sup><sub>6</sub></b>		<b>SCH<sup>+</sup><sub>5,4,3,2,1</sub></b>
	<b>+</b>		<b>+</b>
	<b>ASC<sup>+</sup><sub>6</sub></b>		<b>ASC<sup>+</sup><sub>5,4,3,2,1</sub></b>

882 **CBM<sub>s</sub>** is the Capacity Benefit Margin for the ATC Path that has been scheduled during that  
 883 period.

884 BPA does not maintain CBM and thus sets CBM<sub>s</sub> at zero for all of its paths for all time  
 885 periods.

886 **TRM<sub>U</sub>** is the Transmission Reliability Margin for the ATC Path that has not been released for  
 887 sale (unreleased) as non-firm capacity by the Transmission Service Provider during that  
 888 period.

889 The description of how BPA implements TRM can be found in BPA’s TRMID, which is posted  
 890 on BPAs website.

891 **Postbacks<sub>NF</sub>** are changes to non-firm Available Transfer Capability due to a change in the use  
 892 of Transmission Service for that period, as defined in Business Practices.

893 The section below outlines how BPA calculates Postbacks<sub>NF</sub> for all of its paths for the  
 894 beyond Real-time and the Real-time horizons.

895 **Postbacks<sub>NF</sub> for the Beyond Real-time horizon**

896 BPA automatically recalculates ETC<sub>NF</sub> to account for changes to Transmission Service  
 897 Requests (such as request types of Recall and annulments) for the Beyond Real-time  
 898 horizon. Since these types of changes to Transmission Service Requests are captured in  
 899 ETC<sub>NF</sub>, BPA sets Postbacks<sub>NF</sub> at zero for this horizon.

900 **Postbacks<sub>NF</sub> for the Real-time Horizon**

901 BPA automatically recalculates ETC<sub>NF</sub> to account for changes to Transmission Service  
 902 Requests (such as request types of Recall and annulments) and/or schedules for the Real-  
 903 time Horizon. Since these types of changes to Transmission Service Requests and/or  
 904 schedules are captured in ETC<sub>NF</sub>, BPA sets Postbacks<sub>NF</sub> at zero for this horizon for all paths  
 905 with the exception of AC N>S.



906 For  $ATC_{NF}$  calculations for the AC N>S path in the Real-time horizon, BPA uses a  
907 Postbacks<sub>NF</sub>, expressed as RADJ/ETC. For its hourly AC N>S non-firm calculations, BPA  
908 posts back any unused share of non-firm capacity that is available to BPA by capacity  
909 ownership and other Agreements for the AC N>S, if needed to prevent Curtailments.

910 **Counterflows<sub>NF</sub>** are adjustments to non-firm Available Transfer Capability as determined by  
911 the Transmission Service Provider and specified in its ATCID.

912 Since a schedule provides assurance that the transaction will flow, all counterflows  
913 resulting from firm and non-firm Transmission schedules, excluding tag types dynamic,  
914 pseudo and capacity, are added back to  $ATC_{NF}$  in the Counterflows<sub>NF</sub> component. (MOD-001  
915 R3.2)

916 In BPA's  $ATC_{NF}$  calculations, Counterflows<sub>NF</sub> is expressed as  $SCH_{7,6,5,4,3,2,1}$ , which is the sum  
917 of schedules flowing in the direction counter to the direction of the path.

918 Counterflows are modeled in the ETC Cases used to determine  $ETC_F$  for BPA's flow-based  
919 paths. In instances where the power flow study results in a negative base ETC value, BPA  
920 uses zero as the base ETC for purposes of calculating  $ATC_{NF}$ . This is done to ensure that  
921 BPA does not make capacity available as a result of counterflows that may or may not  
922 materialize in real-time

923 In some cases, the amount of Counterflows<sub>NF</sub> exceeds the sum of the  $ETC_F$  and  $ETC_{NF}$ ,  
924 which, when added to TTC, results in  $ATC_{NF}$  greater than TTC.

925 Note: The variable RADJ/ETC is also used to respond to a BPA dispatcher order to change ATC  
926 values by a specified amount and thereby reduce schedules in-hour when the flow exceeds  
927 the TTC.

## 928 **Adjustments to Flow-based Path ATC Values**

929 There may be instances where BPA needs to perform testing in the production environment of  
930 the systems that manage BPA's ATC calculations. In these instances, BPA may adjust its ATC  
931 values across the flow-based paths to ensure that Hourly requests are not declined due to  
932 lack of ATC across the flow-based paths. BPA will issue a notice to customers with the details  
933 prior to performing this testing.

---

## 934 **VIII. Data Sources and Recipients**

---

935 BPA receives data for use in its ATC calculations, and provides data for use in calculating 1:1  
936 and flow-based path capabilities through the WECC base case process. BPA also directly  
937 receives and provides data, such as outage information and specific Transmission  
938 commitments, from and to the following Transmission Service Providers and Transmission  
939 Operators: (MOD-001 R3.3, R3.4)

- 940 • Avista Corporation
- 941 • BC Hydro
- 942 • California Independent System Operator
- 943 • City of Tacoma, Department of Public Utilities, Light Division

- 944 • Eugene Water and Electric Board
- 945 • Fortis BC
- 946 • Idaho Power Company
- 947 • Los Angeles Department of Water and Power
- 948 • NV Energy
- 949 • NorthWestern Energy
- 950 • Pacific Gas & Electric
- 951 • PacifiCorp
- 952 • Pend Oreille County Public Utility District No. 1
- 953 • Portland General Electric
- 954 • Public Utility District No. 1 of Chelan County
- 955 • Public Utility District No. 1 of Clark County
- 956 • Public Utility District No. 1 of Douglas County
- 957 • Public Utility District No. 2 of Grant County, Washington
- 958 • Public Utility District No. 1 of Snohomish County
- 959 • Puget Sound Energy, Inc.
- 960 • Sacramento Municipal Utility District
- 961 • Seattle City Light
- 962 • Southern California Edison
- 963 • Transmission Agency of Northern California
- 964 • Western Area Power Administration - Sierra Nevada Region
- 965 • California Independent System Operator

---

## 966 IX. Responding to Data Requests

---

967 Upon official request from any Transmission Service Provider, Planning Coordinator,  
 968 Reliability Coordinator, or Transmission Operator for any data from the list below, solely for  
 969 use in the requestor's ATC or AFC calculations, BPA will begin to make the data available  
 970 within 30 calendar days of receiving the request.

- 971 • Expected generation and Transmission outages, additions, and retirements
- 972 • Load forecasts
- 973 • Unit commitments and order of dispatch, to include all designated resources (BPA does  
 974 not have resources that are committed or have the legal obligation to run)
- 975 • Firm NITS and non-firm NITS (i.e. Secondary Service)
- 976 • Firm and non-firm Transmission reservations
- 977 • Grandfathered obligations
- 978 • Firm roll-over rights
- 979 • Any firm and non-firm adjustments applied by BPA to reflect parallel path impacts
- 980 • Power flow models and underlying assumptions
- 981 • Contingencies, provided in one or more of the following formats:

- 982           ○ A list of Elements
- 983           ○ A list of flow-based paths
- 984           ○ A set of selection criteria that can be applied to the WECC base cases used by
- 985           BPA
- 986       • Facility Ratings
- 987       • Any other service that impact ETCs
- 988       • Values of CBM and TRM for all paths
- 989       • Values of TTC and ATC for all paths
- 990       • Source and sink identification and mapping to the WECC base cases

991 BPA will make this data available on the schedule specified by the requestor (but no more  
992 frequently than once per hour, unless mutually agreed to by the requestor and Bonneville).

993 For a Transmission Service Provider, Planning Coordinator, Reliability Coordinator, or  
994 Transmission Operator to officially request data to use in ATC or AFC calculations, the  
995 requestor must fill out the **Data Request Form** (MOD-001 R9) found on BPA's ATC  
996 Methodology website. The completed request form must be sent to  
997 [nercatstandards@bpa.gov](mailto:nercatstandards@bpa.gov) with **Data request Form** (MOD-001 R9) in the subject line. (MOD-  
998 001 R9)

---

---

## 999 X. ATCID Revisions

---

1000 BPA will notify the entities contained in ATCID TP Distribution List when implementing a new  
1001 or revised ATCID and make its current ATCID available. (MOD-001 R4, R5)